

KC007 FBMA-A SERIES

MULTILAYER CHIP BEADS → FBMA-A Series				High Current Type	
ORDERING CODE	Impedance (Ω)	Tol ±	Test Frequency (MHz)	DC Resistance (Ω)max	Rated Current (mA)max
FBMA-11-160808-250A30	25	25%	100	0.040	3000
FBMA-11-160808-300A10	30	25%	100	0.100	1000
FBMA-11-160808-600A30	60	25%	100	0.040	3000
FBMA-11-160808-121A20	120	25%	100	0.100	2000
FBMA-11-160808-121A30	120	25%	100	0.040	3000
FBMA-11-160808-301A20	300	25%	100	0.100	2000
FBMA-11-160808-601A10	600	25%	100	0.200	1000

MULTILAYER CHIP BEADS → FBMA-A Series				High Current Type	
ORDERING CODE	Impedance (Ω)	Tol ±	Test Frequency (MHz)	DC Resistance (Ω)max	Rated Current (mA)max
FBMA-11-201209-100A60	10	25%	100	0.010	6000
FBMA-11-201209-330A40	33	25%	100	0.035	4000
FBMA-11-201209-600A30	60	25%	100	0.040	3000
FBMA-11-201209-800A40	80	25%	100	0.035	4000
FBMA-11-201209-121A40	120	25%	100	0.035	4000
FBMA-11-201209-121A50	120	25%	100	0.020	5000
FBMA-11-201209-221A30	220	25%	100	0.040	3000
FBMA-11-201209-301A10	300	25%	100	0.200	1000
FBMA-11-201209-401A20	400	25%	100	0.100	2000
FBMA-11-201209-601A20	600	25%	100	0.100	2000

MULTILAYER CHIP BEADS → FBMA-A Series				High Current Type	
ORDERING CODE	Impedance (Ω)	Tol ±	Test Frequency (MHz)	DC Resistance (Ω)max	Rated Current (mA)max
FBMA-11-321611-300A60	30	25%	100	0.010	6000
FBMA-11-321611-800A40	80	25%	100	0.035	4000
FBMA-11-321611-121A30	120	25%	100	0.040	3000
FBMA-11-321611-121A50	120	25%	100	0.020	5000
FBMA-11-321611-301A10	300	25%	100	0.200	1000
FBMA-11-321611-501A20	500	25%	100	0.100	2000
FBMA-11-321611-501A30	500	25%	100	0.040	3000
FBMA-11-321611-601A30	600	25%	100	0.040	3000
FBMA-11-322513-151A50	150	25%	100	0.020	5000
FBMA-11-322513-201A40	200	25%	100	0.035	4000
FBMA-11-322513-301A30	300	25%	100	0.040	3000

MULTILAYER CHIP BEADS → FBMA-A Series				High Current Type	
ORDERING CODE	Impedance (Ω)	Tol ±	Test Frequency (MHz)	DC Resistance (Ω)max	Rated Current (mA)max
FBMA-11-451616-600A60	60	25%	100	0.010	6000
FBMA-11-451616-800A40	80	25%	100	0.030	4000
FBMA-11-453215-900A60	90	25%	100	0.010	6000
FBMA-11-453215-900A90	90	25%	100	0.004	9000
FBMA-11-453215-121A40	120	25%	100	0.030	4000
FBMA-11-453215-121A60	120	25%	100	0.010	6000
FBMA-18-453215-121A90	120	25%	100	0.004	9000
FBMA-11-453215-151A50	150	25%	100	0.020	5000